

# KB - Polycom Conference Room SoundStation IP 6000

## 1. Manual Configuration

1. On the Phone pick **Menu > Status > Network > TCP/IP Parameters**
2. Document IP address

Log into the Local Network via the **TCP/IP Parameters**

1. Login As: **Admin**
2. Password: [REDACTED]

Go to **Settings > Lines**

### Identification

- Display Name: {Ext#}
- Address: {Ext#}
- Authentication User ID: {Ext#}
- Authentication Password: [REDACTED]
- Label: {Ext#}
- Type: Private
- Third Party Name: [Blank]
- Number of Line Keys: 1
- Calls per line: 8
- Ring Type: Low Trill

### Server 1

- Address: {IP Address of the PBX}
- Port: [REDACTED]
- Transport: DNSnaptr
- Expires (s): 120
- Register: Yes
- Retry Timeout (ms): 0
- Retry Maximum Count: 3
- Line Seize Timeout (s): 30

Click **Save**

Back in the PBX

1. **Server > Diagnostics > Connection Status**
2. Find the Ext and confirm the user agent shows the **IP6000** as **Registered**